


# NI10U-M12E-VP6X

## Inductive Sensor – With Extended Switching Distance




### Features

- M12 × 1 threaded barrel
- Long version
- Chrome-plated brass
- Factor 1 for all metals
- Protection class IP68
- Resistant to magnetic fields
- Large switching distance
- Integrated protection against predamping
- Little metal-free spaces
- DC 4-wire, 10...30 VDC
- Changeover contact, PNP output
- Cable connection

### Technical data

|                                           |                                                                                    |
|-------------------------------------------|------------------------------------------------------------------------------------|
| Type                                      | NI10U-M12E-VP6X                                                                    |
| ID                                        | 100000621                                                                          |
| <b>General data</b>                       |                                                                                    |
| Rated switching distance                  | 10 mm                                                                              |
| Mounting conditions                       | Non-flush                                                                          |
| Secured operating distance                | $\leq (0.81 \times S_n)$ mm                                                        |
| Repeat accuracy                           | $\leq 2 \%$ of full scale                                                          |
| Temperature drift                         | $\leq \pm 10 \%$<br>$\leq \pm 15 \%, \leq -25 \text{ °C} \vee \geq +70 \text{ °C}$ |
| Hysteresis                                | 3...15 %                                                                           |
| <b>Electrical data</b>                    |                                                                                    |
| Operating voltage                         | 10...30 VDC                                                                        |
| Residual ripple                           | $\leq 10 \%$ $U_{ss}$                                                              |
| DC rated operational current              | $\leq 200$ mA                                                                      |
| No-load current                           | 15 mA                                                                              |
| Residual current                          | $\leq 0.1$ mA                                                                      |
| Isolation test voltage                    | $\leq 0.5$ kV                                                                      |
| Short-circuit protection                  | yes / Cyclic                                                                       |
| Voltage drop at $I_o$                     | $\leq 1.8$ V                                                                       |
| Wire breakage/Reverse polarity protection | yes / Complete                                                                     |
| Output function                           | 4-wire, Complementary contact, PNP                                                 |
| DC field stability                        | 300 mT                                                                             |
| AC field stability                        | 300 mT <sub>ss</sub>                                                               |
| Switching frequency                       | 1 kHz                                                                              |
| <b>Mechanical data</b>                    |                                                                                    |
| Design                                    | Threaded barrel, M12 x 1                                                           |

### Wiring diagram



### Functional principle

Inductive sensors are designed for wear-free and contactless detection of metal objects. uprox+ sensors have significant advantages due to their patented multi-coil system. They excel thanks to their optimum switching distances, maximum flexibility and operational reliability as well as efficient standardization.

Technical data

|                                       |                                           |
|---------------------------------------|-------------------------------------------|
| Dimensions                            | 64 mm                                     |
| Housing material                      | Metal, CuZn, Chrome-plated                |
| Active area material                  | Plastic, LCP                              |
| End cap                               | Plastic, EPTR                             |
| Max. tightening torque of housing nut | 10 Nm                                     |
| Electrical connection                 | Cable                                     |
| Cable quality                         | Ø 5.2 mm, Gray, LifYY, PVC, 2 m           |
| Core cross-section                    | 4 x 0.34 mm <sup>2</sup>                  |
| Environmental conditions              |                                           |
| Ambient temperature                   | -30...+85 °C                              |
| Vibration resistance                  | 55 Hz (1 mm)                              |
| Shock resistance                      | 30 g (11 ms)                              |
| Protection class                      | IP68                                      |
| MTTF                                  | 874 years acc. to SN 29500 (Ed. 99) 40 °C |
| Switching state                       | LED, Yellow                               |

Mounting instructions

## Mounting instructions/Description

The diagrams illustrate different mounting methods for the sensor. The top-left diagram shows a sensor mounted on a plate with a dimension line labeled 'T' indicating the distance from the sensor's center to the edge of the plate. The middle-left diagram shows two sensors mounted on a plate with a dimension line labeled 'G' indicating the distance between the centers of the two sensors. The bottom-left diagram shows two sensors mounted on a plate with dimension lines labeled 'N', 'S', 'D', and 'W' indicating various distances: 'N' is the distance from the sensor's center to the top edge of the plate, 'S' is the distance from the sensor's center to the bottom edge of the plate, 'D' is the distance from the sensor's center to the center of the other sensor, and 'W' is the width of the plate. The top-right diagram shows a sensor mounted on a plate with a dimension line labeled 'X' indicating the distance from the sensor's center to the edge of the plate. The bottom-right diagram shows a sensor mounted on a plate with a dimension line labeled 'X' indicating the distance from the sensor's center to the edge of the plate.





The top-right diagram shows a sensor mounted on a plate with a dimension line labeled 'X' indicating the distance from the sensor's center to the edge of the plate. The bottom-right diagram shows a sensor mounted on a plate with a dimension line labeled 'X' indicating the distance from the sensor's center to the edge of the plate.

|                        |         |
|------------------------|---------|
| Distance D             | 4 x B   |
| Distance W             | 3 x Sn  |
| Distance T             | 3 x B   |
| Distance S             | 1.5 x B |
| Distance G             | 6 x Sn  |
| Distance N             | 2 x Sn  |
| Diameter active area B | Ø 12 mm |

All non-flush mountable uprox®+ threaded barrel sensors can be screwed to the upper edge of the barrel. In this mounting position, the sensor operates safely with a 20 % reduced switching distance.

When installed in an aperture plate a distance of X = 50 mm must be observed.

Accessories

|                                                                                   |                                                                                              |                                                                                    |                                                                                                                                                                                            |
|-----------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| BST-12B                                                                           | 6947212                                                                                      | QM-12                                                                              | 6945101                                                                                                                                                                                    |
|  | Mounting clamp for threaded barrel sensors, with dead-stop; material: PA6                    |  | Quick-mount bracket with dead-stop; material: Chrome-plated brass. Male thread M16 × 1. Note: The switching distance of the proximity switches may change when using quick-mount brackets. |
| MW-12                                                                             | 6945003                                                                                      | BSS-12                                                                             | 6901321                                                                                                                                                                                    |
|  | Mounting bracket for threaded barrel sensors; material: Stainless steel A2 1.4301 (AISI 304) |  | Mounting clamp for smooth and threaded barrel sensors; material: Polypropylene                                                                                                             |