


QS30FF400QPMA16 Photoelectric Sensor – Diffuse Mode Sensor with Fixed-Field Background Suppression






| Туре | QS30FF400QPMA16 |
|------------------------------|--------------------------------------------|
| ID no. | 3073090 |
| Optical data | |
| Function | Proximity switch |
| Operating mode | Background suppression, non-adjustable |
| Light type | Red |
| Wavelength | 680 nm |
| Range | 0400 mm |
| Electrical data | |
| Operating voltage | 1030 VDC |
| Residual ripple | < 10 % U _{ss} |
| DC rated operational current | ≤ 150 mA |
| No-load current | ≤ 35 mA |
| Short-circuit protection | yes |
| Reverse polarity protection | yes |
| Output function | NO contact, PNP/NPN |
| Switching frequency | ≤ 250 Hz |
| Readiness delay | ≤ 100 ms |
| Response time typical | < 2 ms |
| Mechanical data | |
| Design | Rectangular with thread, QS30 |
| Dimensions | Ø 30 x 35 x 22 x 49 mm |
| Housing material | Plastic, Thermoplastic material, Yellow |
| Lens | plastic, Acrylic |
| Electrical connection | Cable with connector, M12 × 1, 0.15 m, PUR |




Features

- Cable with male end M12 × 1, 5-pin, PUR, 150 mm
- Protection class IP67
- ■LED all-round visible
- Operating voltage: 10...30 VDC
- ■Switching output, bipolar
- Light or dark operation

Wiring diagram






Functional principle

Diffuse mode sensors with background suppression operate with a single emitter and several receiver elements. The target position and the photoelectric structure of the sensor determine which of the receiving elements receives the most light. The sensor electronics determine whether the reflecting object is within or outside the measuring range. These sensors come with a fixed cut-off point.

Excess gain curve Excess gain in relation to the distance

Technical data


| Number of cores | 5 |
|------------------------|-------------------------------------------|
| Ambient temperature | -20+70 °C |
| Protection class | IP67 |
| Power-on indication | LED, Green |
| Switching state | LED, Yellow |
| Error indication | LED, green, Flashing |
| Excess gain indication | LED, yellow |
| Tests/approvals | |
| MTTF | 177 years acc. to SN 29500 (Ed. 99) 40 °C |
| Approvals | CE |




Accessories

| SMB30A |
|-----------------------------|
| Ø 30,5 6,3 wide Ø 6,3 |
| 7,5 |

3032723 Mounting bracket, rectangular, stainless steel, for sensors with 30mm thread



3002809 Mounting bracket, stainless steel, for QS30 series



Mounting bracket, rectangular, stainless steel, for sensors with 30 mm thread, wide holes for accurate alignment

3027162



Mounting bracket, PBT black, for sensors with 30 mm thread, rotatable

3052521



Accessories

