

RU100U-M18M-UP8X2-H1151 Ultrasonic Sensor – Diffuse Mode Sensor



Technical data

Туре	RU100U-M18M-UP8X2-H1151		
ID	1610010		
Ultrasonic data			
Function	Proximity switch		
Range	1501000 mm		
Resolution	1 mm		
Minimum switching range	10 mm		
Ultrasound frequency	200 kHz		
Repeat accuracy	≤ 0.15 % of full scale		
Temperature drift	± 1.5 % of full scale		
Linearity error	≤ ± 0.5 %		
Edge lengths of the nominal actuator	100 mm		
Approach speed	≤ 8 m/s		
Pass speed	≤ 2 m/s		
Electrical data			
Operating voltage	1530 VDC		
Residual ripple	10 % U _{ss}		
DC rated operational current	≤ 150 mA		
No-load current	≤ 50 mA		
Load resistance	≤ 1000 Ω		
Residual current	≤ 0.1 mA		
Response time typical	< 90 ms		
Readiness delay	≤ 300 ms		
Output function	NO/NC, PNP		
Output 1	Switching output		
Switching frequency	≤ 6.9 Hz		
Hysteresis	≤ 10 mm		

Features

- Smooth sonic transducer face
- Cylindrical housing M18, potted
- Connection via M12 x 1 male
- Temperature compensation
- Blind zone: 15 cm
- Range: 100 cm
- Resolution: 1 mm
- Aperture angle of sonic cone: ±16 °
- 1 × switching output, PNP
- Teachable settings
- NO/NC programmable

Wiring diagram



Functional principle

Ultrasonic sensors capture a multitude of objects contactlessly and wear-free with ultrasonic waves. It does not matter whether the object is transparent or opaque, metallic or non-metallic, firm, liquid or powdery. Even environmental conditions such as spray, dust or rain hardly affect their function. The sonic cone diagram indicates the detection range of the sensor. In accordance with standard EN 60947-5-2, quadratic targets in a range of sizes (20 × 20 mm, 100 × 100 mm) and a round rod with a diameter of 27 mm are used.

Important: The detection ranges for other targets may differ from those for standard targets due to the different reflection properties and geometries.

Sonic Cone





Technical data

Voltage drop at I_{\circ}	≤ 2.5 V
Short-circuit protection	yes / Cyclic
Reverse polarity protection	yes
Wire breakage protection	yes
Setting option	Remote Teach
Mechanical data	
Design	Threaded barrel, M18
Radiation direction	straight
Dimensions	Ø 18 x 63 mm
Housing material	Metal, CuZn, Nickel Plated
Max. tightening torque of housing nut	20 Nm
Transducer material	Plastic, Epoxyd resin and PU foam
Electrical connection	Connector, M12 × 1, 5-wire
Ambient temperature	-25+70 °C
Storage temperature	-40+80 °C
Pressure resistance	0.55 bar
Protection class	IP67
Switching state	LED, Yellow
Object detected	LED, Green
Tests/approvals	
MTTF	281 years acc. to SN 29500 (Ed. 99) 40 °C
Declaration of conformity EN ISO/IEC	EN 60947-5-2
Vibration resistance	IEC 60068-2
Approvals	CE cULus

Mounting instructions



The ultrasonic sensor features a switching output with a teachable switching point. The green and yellow LEDs indicate whether the

One switching point is taught. This must be within the detection range. In this operating mode the background is suppressed.

Connect the TX1-Q20L60 teach adapter between the sensor and connection cable Place object at the end of the switching range Press and hold button for at least 2 s against

After a successful teach-in, the green LED flashes at 3 Hz and the sensor runs

the button against the Ub for 2...7s



LED response

In standard operating mode, the two LEDs indicate the switching state of the sensor. Green: Object within the detection range but not in switching range Yellow: Object is within the switching range

Off: Object is outside the detection range or signal loss

Accessories



6945004 Mounting bracket for threaded barrel sensors; material: Stainless steel A2 1.4301 (AISI 304)

Accessories



Accessories

Dimension drawing	Туре	ID	
	TX1-Q20L60	6967114	Teach adapter for inductive encoders, linear position, angle, ultrasonic and capacitive sensors