





OLD

NEW

Power to unlock

AZM 161...-24...



(2 NO / 4 NC contacts)



A1 A2

AZM 161...-33...

(3 NO / 3 NC contacts)





A1 A2

		Old	New
<b>Actuator contacts</b>	NO	13-14	13-14
	NC	21-22	21-22
	NC	31-32	–
	NC	41-42	41-42
<b>Magnet contacts</b>	NC	51-52	51-52
	NO	63-64	63-64
	NC	–	71-72
<b>Magnet voltage</b>		A1-A2	A1-A2

AZM 161...-12/12...

(2 NO / 4 NC contacts)





		Old	New
<b>Actuator contacts</b>	NO	13-14	13-14
	NC	21-22	21-22
	NO	33-34	–
	NC	41-42	41-42
<b>Magnet contacts</b>	NC	51-52	51-52
	NO	63-64	63-64
	NC	–	71-72
<b>Magnet voltage</b>		A1-A2	A1-A2

Power to lock

AZM 161...-24...A



(2 NO / 4 NC contacts)



A1 A2

AZM 161...-33...A

(3 NO / 3 NC contacts)





A1 A2

		Old	New
<b>Actuator contacts</b>	NO	13-14	13-14
	NC	21-22	21-22
	NC	31-32	–
	NC	41-42	41-42
<b>Magnet contacts</b>	NC	51-52	51-52
	NO	63-64	63-64
	NC	–	71-72
<b>Magnet voltage</b>		A1-A2	A1-A2

AZM 161...-12/12...A

(2 NO / 4 NC contacts)



		Old	New
<b>Actuator contacts</b>	NO	13-14	13-14
	NC	21-22	21-22
	NO	33-34	–
	NC	41-42	41-42
<b>Magnet contacts</b>	NC	51-52	51-52
	NO	63-64	63-64
	NC	–	71-72
<b>Magnet voltage</b>		A1-A2	A1-A2

Key

- ⊖ Positive break NC contact
- ⊕ Monitoring the interlock according to EN ISO 14119

**K.A. Schmersal GmbH & Co. KG**  
Mödinghofe 30, 42279 Wuppertal  
Germany  
Phone: +49 202 6474-0  
Telefax: +49 202 6474-100  
E-Mail: info@schmersal.com  
Internet: www.schmersal.com