

Inductive Sensor With Extended Switching Distance BI15U-M30-VP44X



1 kHz

M30 × 1.5 threaded tube .

- Resistant to magnetic fields
- Large switching distance
- Changeover contact, PNP output



Inductive sensors are designed for wear-free and contactless detection of metal objects. uprox+ sensors have significant advantages due to their patented multi-coil system. They excel thanks to their optimum switching distances, maximum flexibility and operational reliability as well as efficient standardization.

Switching frequency



Mechanical data			
Design	Threaded barrel, M30 x 1.5		
Dimensions	64 mm		
Housing material	Metal, CuZn, Chrome-plated		
Active area material	Plastic, LCP		
End cap	Plastic, EPTR		
Max. tightening torque of housing nut	75 Nm		
Electrical connection	Cable		
Cable quality	Ø 5.2 mm, Gray, LifYY, PVC, 2 m		
Core cross-section	4 x 0.34 mm ²		
Environmental conditions			
Ambient temperature	-30+85 °C		
Vibration resistance	55 Hz (1 mm)		
Shock resistance	30 g (11 ms)		
Protection class	IP68		
MTTF	874 years acc. to SN 29500 (Ed. 99) 40 °C		
Switching state	LED, Yellow		

Hans Turck GmbH & Co.KG • D-45472 Mülheim an der Ruhr • Witzlebenstraße 7 • Tel. 0208 4952-0 • Fax 0208 4952-264 • more@turck.com • www.turck.com2 / 3



Accessories

Type code	Ident no.		Dimension drawing
PN-M30	6905308	Protective nut for M30 x 1 threaded barrel devices; material: Stainless steel A2 1.4305 (AISI 303)	→ M30 x 1,5
BST-30B	6947216	Mounting clamp for threaded barrel sensors, with dead-stop; material: PA6	M5 20 6 30 30 30
QM-30	6945103	Quick-mount bracket with dead-stop; material: Chrome-plated brass. Male thread M36 × 1.5. Note: The switching distance of the proximity switches may change when using quick- mount brackets.	41/6 0 30 -20,5 36
MW-30	6945005	Mounting bracket for threaded barrel sensors; material: Stain- less steel A2 1.4301 (AISI 304)	5.5 11.2 34,8 57.2 10.3 2.2
BSS-30	6901319	Mounting clamp for smooth and threaded barrel sensors; ma- terial: Polypropylene	