

Inductive Sensor With Extended Switching Distance BI8U-Q08-AP6X2-0.6-RS4/S1160



Туре BI8U-Q08-AP6X2-0.6-RS4/S1160 ID 1662028 Special version S1160 corresponds to: Weld-resistant cable General data Rated switching distance Sn 8 mm Mounting conditions Flush Secured operating distance ≤ (0.81 × Sn) mm Repeat accuracy \leq 2 % of full scale Temperature drift $\leq \pm 10$ % Hysteresis 3...15 % Electrical data Operating voltage 10...30 VDC Residual ripple \leq 10 % U_{ss} DC rated operational current \leq 200 mA Residual current ≤ 0.1 mA Isolation test voltage $\leq 0.5 \text{ kV}$ Short-circuit protection yes/ Cyclic Voltage drop at I \leq 1.8 V Wire breakage/Reverse polarity protection yes/ Complete Output function 3-wire, NO contact, PNP DC field stability 300 mT AC field stability 300 mT_{ss} 0.25 kHz Switching frequency Mechanical data Design Rectangular, Q08





- Rectangular, height 8 mm
- Active face on top
- Metal, Zamak, nickel-plated
- Factor 1 for all metals
- Increased switching distance
- Protection class IP68
- Resistant to magnetic fields
- Mountable on metal
- DC 3-wire, 10...30 VDC
- NO contact, PNP output
- Pigtail with male end M12 x 1

Wiring Diagram



Functional principle

Inductive sensors are designed for wear-free and contactless detection of metal objects. uprox+ sensors have significant advantages due to their patented multi-coil system. They excel thanks to their optimum switching distances, maximum flexibility and operational reliability as well as efficient standardization.



Environmental conditions	
Ambient temperature	-25+70 °C
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 g (11 ms)
Protection class	IP68
MTTF	874 years acc. to SN 29500 (Ed. 99) 40 °C
Power-on indication	LED, Green
Switching state	LED, Yellow

Hans Turck GmbH & Co.KG • D-45472 Mülheim an der Ruhr • Witzlebenstraße 7 • Tel. 0208 4952-0 • Fax 0208 4952-264 • more@turck.com • www.turck.com2 / 2